



BEAMZ
MADE
EAZY

V1.0
153.291

BS340
USER MANUAL

CONTROL MENU

MENU	Parameter	Value / Option	Description
Addr	A001-A512		DMX Address selection
Chnd	12/70ch		Channel selection
Mode	Mast/d512		Host mode selection
Soun	So 0-20		Sound control program selection 0-20
	Se 99-0		Sound control sensitivity adjustment
Auto	Aut 0-20		Auto effect selection
	SP 1-9		Auto effect speed adjustment
RF	ON/OFF		Remote control on/off selection
dISP	dISP		Digital display flip setting
t-30			Displays the the temperature of the unit
ver	V10	Vxxxx.xx	Current software version
Load	No/Yes		load program

DMX CHANNELS

12 CHANNELS

Channel	Function	Value	Channels description
CH1	Total dimmer	000-255	0%- 100%
CH2	No function	000-008	0%- 100%
	Strobe speed slow to fast	009-255	0%- 100%
CH3	CCT (See CCT Table)	000-255	0%- 100%
CH4	Amber dimmer	000-255	0%- 100%
CH5	Cool white dimmer	000-255	0%- 100%
CH6	Red dimmer	000-255	0%- 100%
CH7	Green dimmer	000-255	0%- 100%
CH8	Blue dimmer	000-255	0%- 100%
CH9	Program (See Program Table)	000-255	Cool white + Amber
CH10	Program Speed slow to fast	000-255	
CH11	Program (See Program Table)	000-255	RGB
CH12	Program Speed slow to fast	000-255	

70 CHANNELS

Channel	Function	Value	Channels description
CH1	Total dimmer	000-255	0%- 100%
CH2	No function	000-008	
	Strobe speed	009-255	slow to fast
CH3	Amber dimmer 1	000-255	Cool white + Amber 0%- 100%
CH4	Cool white dimmer 1	000-255	
CH5	Amber dimmer 2	000-255	
CH6	Cool white dimmer 2	000-255	
CH7	Amber dimmer 3	000-255	
CH8	Cool white dimmer 3	000-255	
CH9	Amber dimmer 4	000-255	
CH10	Cool white dimmer 4	000-255	
CH11	Amber dimmer 5	000-255	
CH12	Cool white dimmer 5	000-255	
CH13	Amber dimmer 6	000-255	
CH14	Cool white dimmer 6	000-255	
CH15	Amber dimmer 7	000-255	
CH16	Cool white dimmer 7	000-255	
CH17	Amber dimmer 8	000-255	
CH18	Cool white dimmer 8	000-255	
CH19	Red dimmer 1	000-255	RGB 0%- 100%
CH20	Green dimmer 1	000-255	
CH21	Blue dimmer 1	000-255	
CH22	Red dimmer 2	000-255	
CH23	Green dimmer 2	000-255	
CH24	Blue dimmer 2	000-255	
CH25	Red dimmer 3	000-255	
CH26	Green dimmer 3	000-255	
CH27	Blue dimmer 3	000-255	
CH28	Red dimmer 4	000-255	
CH29	Green dimmer 4	000-255	
CH30	Blue dimmer 4	000-255	

CH31	Red dimmer 5	000-255	
CH32	Green dimmer 5	000-255	
CH33	Blue dimmer 5	000-255	
CH34	Red dimmer 6	000-255	
CH35	Green dimmer 6	000-255	
CH36	Blue dimmer 6	000-255	
CH37	Red dimmer 7	000-255	
CH38	Green dimmer 7	000-255	
CH39	Blue dimmer 7	000-255	
CH40	Red dimmer 8	000-255	
CH41	Green dimmer 8	000-255	
CH42	Blue dimmer 8	000-255	
CH43	Red dimmer 9	000-255	
CH44	Green dimmer 9	000-255	
CH45	Blue dimmer 9	000-255	
CH46	Red dimmer 10	000-255	
CH47	Green dimmer 10	000-255	
CH48	Blue dimmer 10	000-255	
CH49	Red dimmer 11	000-255	
CH50	Green dimmer 11	000-255	
CH51	Blue dimmer 11	000-255	
CH52	Red dimmer 12	000-255	
CH53	Green dimmer 12	000-255	
CH54	Blue dimmer 12	000-255	
CH55	Red dimmer 13	000-255	
CH56	Green dimmer 13	000-255	
CH57	Blue dimmer 13	000-255	
CH58	Red dimmer 14	000-255	
CH59	Green dimmer 14	000-255	
CH60	Blue dimmer 14	000-255	
CH61	Red dimmer 15	000-255	
CH62	Green dimmer 15	000-255	
CH63	Blue dimmer 15	000-255	
CH64	Red dimmer 16	000-255	
CH65	Green dimmer 16	000-255	
CH66	Blue dimmer 16	000-255	
CH67	Program (See Program Table)	000-255	Cool white + Amber
CH68	Program Speed	000-255	slow to fast
CH69	Program (See Program Table)	000-255	RGB
CH70	Program Speed	000-255	slow to fast

PROGRAM AND CCT TABLE


PROGRAM TABLE

Program	Function
000-007	No Function
008-019	Program1
020-031	Program2
032-043	Program3
044-055	Program4
056-067	Program5
068-079	Program6
080-091	Program7
092-103	Program8
104-115	Program9
116-127	Program10
128-139	Program11
140-151	Program12
152-163	Program13
164-175	Program14
176-187	Program15
188-199	Program16
200-211	Program17
212-223	Program18
224-235	Program19
235-247	Program20
248-255	Sound Standalone


CCT TABLE

CCT	Function
000 - 009	No function
010 - 029	2.200K
030 - 049	2.400K
050 - 069	2.800K
070 - 089	3.200K
090 - 109	3.600K
110 -129	4.000K
130 - 149	5.200K
150 - 169	5.400K
170 - 189	6.000K
190 - 209	6.400K
210 - 229	6.800K
230 - 255	7.200K

NOTES



NOTES





BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

BEAMZLIGHTING.COM