



BEAMZ
MADE
EAZY

153.804 V1.0

SHOWBAR FREE2

QUICK START GUIDE

CONTROL MENU

MENU	DESCRIPTION	
DMX ADDR	A001-A512	DMX address setting
CHANNEL	DMX	3CH
		24CH
RUNMODE	DMX512	Master-Slave
	Master	
SO LOST	On/Off	Sound lost
SOUND	Pro 0-7	8 Sound combo Programs
	Se 0-99	Sensitivity
AUTO	Pro 0-7	8 Auto Combo Programs
	Sp 1-9	Speed for Auto Programs
DISPLAY	On/Off	
VERSION	XXX	
DEFAULT	YES/NO	Reset Device

DMX CHANNELS

3 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
		000-009	No Function
		010-069	Mixed Program
		070-089	Par1&Par2
		090-109	Derby1&Derby2
2	AUTO MODE	110-129	White Strobe
		130-189	Mixed Program
		190-209	Par1&Par2
		210-229	Derby1&Derby2
		230-255	White Strobe
3	SPEED & SENSITIVITY	000-255	Slow to fast (CH2 in Auto mode)
			(CH2 in Sound mode)

24 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
2	PAR STROBE	000-009	No Function
		010-255	Par Strobe from Slow to Fast
3	PAR1 RED	000-255	Dimmer Red 0-100%
4	PAR1 GREEN	000-255	Dimmer Green 0-100%
5	PAR1 BLUE	000-255	Dimmer Blue 0-100%
6	PAR1 WHITE	000-255	Dimmer White 0-100%
7	PAR2 RED	000-255	Dimmer Red 0-100%
8	PAR2 GREEN	000-255	Dimmer Green 0-100%
9	PAR2 BLUE	000-255	Dimmer Blue 0-100%
10	PAR2 WHITE	000-255	Dimmer White 0-100%
11	DERBY STROBE	000-009	No Function
		010-255	Par Strobe from Slow to Fast
12	DERBY1 RED	000-255	Dimmer Red 0-100%
13	DERBY1 GREEN	000-255	Dimmer Green 0-100%

14	DERBY1BLUE	000-255	Dimmer Blue 0-100%
15	DERBY1 WHITE	000-255	Dimmer White 0-100%
16	DERBY2 RED	000-255	Dimmer Red 0-100%
17	DERBY2 GREEN	000-255	Dimmer Green 0-100%
18	DERBY2 BLUE	000-255	Dimmer Blue 0-100%
19	DERBY2 WHITE	000-255	Dimmer White 0-100%
20	DERBY MOTOR SPEED	000-009	No Function
		010-255	Derby Motor Speed from Slow to Fast
21		000-255	Dimmer 0-100%
22	WHITE STROBE	000-015	Open
		016-131	Strobe-slow to fast
		132-139	Open
		140-181	Slow on-Fast off, speed slow to fast
		182-189	Open
		190-231	Fast on-Slow off, speed slow to fast
		232-247	Random Strobe
		248-255	Open
23	AUTO MODE	000-009	No Function
		010-069	Mixed Programs
		070-089	Par1&Par2
		090-109	Derby1&Derby2
	SOUND MODE	110-129	White Strobe
		130-189	Mixed Programs
		190-209	Par1&Par2
		210-229	Derby1&Derby2
24	SPEED & SENSITIVITY	000-255	White Strobe
			Speed, Slow to Fast (CH23 in auto mode) Sound Sensitivity (CH23 in sound mode)



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.



BEAMZLIGHTING.COM